



VP-1201

12x1 RGBHV Switcher



Compatible with HDTV component video signals when used with a breakout cable such as the Kramer C-GM/3RVF.



The **VP-1201** is a high performance switcher/scanner for computer graphics video signals. When configured as a scanner, it will cycle through selected inputs at pre-determined intervals.

FEATURES

- Bandwidth - 400MHz (- 3dB).
- HDTV Compatible.
- Dual Mode - Configure as a 12x1 switcher or scanner.
- Expandable - Cascade up to eight units for an input expansion configuration.
- Active Input Indication™ reporting - Each input button on the front panel automatically lights up when the unit detects a video signal on that input. When an input is selected to be switched, the button changes to a different color to indicate that it is the active input.
- Scanner Mode Dwell Time - Adjustable from 1-16 seconds.
- Control - Front panel, RS-232, RS-485 and Ethernet.
- Standard 19" Rack Mount Size - 1U.



VP-1201

TECHNICAL SPECIFICATIONS

INPUTS:	12 XGA inputs on HD15F connectors
OUTPUT:	1 XGA output on an HD15F connector
MAX. OUTPUT LEVEL:	1.9Vpp
BANDWIDTH (-3dB):	400MHz
DIFF. GAIN:	0.03%
DIFF. PHASE:	0.05 Deg.
K-FACTOR:	< 0.05%
S/N RATIO:	76dB
CROSSTALK (all hostile):	-61dB @ 5MHz
CONTROLS:	-1.3dB to + 6dB, RGB level control
COUPLING:	DC
POWER SOURCE:	230 VAC, 50/60 Hz (115 VAC, USA)
DIMENSIONS:	19 inch (W), 7 inch (D), 1U (H) rack mountable
WEIGHT:	5.5 kg. (12.2 lbs.) approx.
ACCESSORIES:	Power cord, Null modem adapter, Windows® based control software, Windows® based Configuration Manager XPort software and Com Port Redirector

