## **JOYSTICK MODELS**





### **S05A**

Our ultra compact proportional thumb rocker. Ideal for integration into professional armrests or grips etc. Unique sealable design.



## **Specifications**

#### **Mechanical performances**

**Electrical performances** 


Operating force: ~14 – 30 mNm Life expectancy: ~ 10,000,000 operations Seal: IP65

Sensor technology: Hall effect, ratiometric Current consumption: ~7 mA per output Independent linearity tolerance: ±3% FS

EMC: 100 V/m

P/N configurations, further specifications and options, please see our Position Sensors catalogue.

#### Terminal connection diagram: Hall effect





## Tailored product examples



Special handle with including S05 sensor having dual output of 25 to 75% applied voltage.



5-axis joystick with special handle incorporating 3 proportional S05 sensors and 5 pushbuttons.



S05 unit with knob and preprogrammed for easy assembly at dashboard.

Subject to change without prior notice. We refer to our general terms and conditions





# **JOYSTICK MODELS**








## **S05A**


### Standard dimensions S05A-H0050-CS


(unit: mm)














 Contact:
 e-mail info@caldaro.com
 Main +46 (0)8 736 1270

 internet www.caldaro.com
 United Kingdom 0800 169 7950

 © Caldaro - JAI
 Germany +49 (0)6136 760 5600

